2307LR

San mar nan

Miniature L-Band/Wideband Fiber Optic Receiver

The 2307LR is a fiber optic receiver in a revolutionary form factor. With the same diameter as a BNC connector, and overall length of 3.3" (85mm), the 2307LR is the smallest RF optical receiver in the industry. It accepts an optical LC connector input on one end, and provides an electrical output on the other.


The 2307LR attaches to the input of a device without any intermediate cabling required. This essentially offers direct optical input to the connected piece of equipment, without incurring the cost and rack space associated with using conventional optical receivers. The primary application is in providing direct optical inputs to XRF series routers, without requiring external fiber receiver cards.

The 2307LR receives its power from the same connector that attaches to the input of the companion device, therefore the 2307LR may also be interfaced to any device that provides LNB voltage at its RF input connector. For example, when connected to a 7703DA16–RF–LNB, a fiber receiver with 16x electrical outputs is created. A 2307LR connected to the input of a 7703PA–LNB results in a fiber receiver with a high–powered output and adjustable slope compensation. The 2307LR may also be connected to the DC–biased inputs of devices such as IRD's, facilitating direct optical input via high–performance optical infrastructure.

Applications

٠

- Direct optical inputs to XRF routers
 - Direct optical inputs to IRDs and other devices with LNB bias
- Distribution amplifiers with optical input
- Line amps/slope compensators with optical input





Features & Benefits

- Compact, efficient form factor provides fiber receiver functionality in zero rack space
- Provides high-quality, direct optical input to XRF series routers and other devices with DC-biased RF input ports
- Wide frequency range for L–Band, over–the–air DTV and other applications
- Tri–color LED optical input strength indicator
- Efficient design featuring high reliability and low power consumption
- Protocol independent passes any modulation format
- Minimizes the use of coax in the infrastructure, providing the highest possible quality signals over longer distances and without high–frequency rolloff
- Compatible with Evertz 2408LT, 7708LT and 7807LT–2 series fiber transmitters

🗅 in @Evertz

REV. 22-1 • PRODUCT DATA SHEET • EVERTZ MICROSYSTEMS LTD.

2307LR

Miniature L-Band/Wideband Fiber Optic Receiver



Specifications **Ordering Information** RF Outputs: Number of Outputs: 1 2307LR Miniature L-band/Wideband fiber receiver Connector: BNC per IEC 61169-8 2307LR-B50 Miniature L-band/Wideband fiber receiver. BNC 50 Ohm Connector Annex A 75Ω, 50Ω optional I/O Impedence: Frequency Range: 40MHz to 3GHz Return Loss: 120MHz-2.3GHz: > 15dB 2.3–3GHz: > 12dB IP3 + 40dBm Output: Link Gain: -6dB at 0dBm optical input, and 0dB gain at the fiber tansmitter **Optical Input:** Number of Inputs: 1 Female LC/UPC Connector: Operating Wavelength: 1270–1610nm Max. Input Power: +3dBm Optical Sensitivity: -14dBm @ 35dB C/N on a 36MHz carrier DC Input: 13V DC nominal, Voltage: range 9–21V DC BNC per IEC 61169–8 Connector: Annex A (same connector as RF output) Power: < 1W Physical: Dimensions: 3.3" length, 0.57" dia. (84mm length, 15mm dia.)

Copyright © Evertz Microsystems Ltd., all rights reserved. Information contained in this document is confidential, privileged and only for the information of the intended recipient; this file may not otherwise be used, published or redistributed without the prior written consent of Evertz Microsystems. Please consider the environment before printing this proprietary document.