

# XTREME 160-C

## 160 Port Fan-In L-Band RF Matrix Switch



XTREME 160-C

### General Description:

The **XTREME 160-C** next generation L-band matrix switch features up to 160 ports in a compact 4 RU chassis. The **XTREME 160-C** is a full fan-in (combining), non-blocking switch where one or multiple inputs can be routed to an output. The **XTREME 160-C** features an industry exclusive flexible matrix architecture (patented) that supports both symmetric and asymmetric configurations of 160 combined inputs and outputs in a single chassis. Asymmetric configurations such as 128x32 can be implemented as well as the standard 64x64 configuration. The **XTREME 160-C** is designed for maximum reliability with redundant power supplies and control cards.

### Features & Benefits:

- Compact modular design with a variety of configurations adding to 160 ports in 4 RU
- Easy hot-swap of all RF cards, power supplies and control cards
- Option for fiber optic inputs
- Independent input and output gain control
- Remotely controlled via web browser GUI interface, SNMP, Telnet or TCP/IP via customer supplied PC
- Redundant hot-swap control cards

| Specifications: *1            | XTREME 160-C  |
|-------------------------------|---|
| Configurations:               | 64x64, 80x48, 128x32  |
| RF Connectors:                | F-Type, BNC 75 Ω or 50 Ω, SMA, Mixed or Optical Input Receivers SC/APC or LC/APC        |
| Impedance:                    | 75 Ω or 50 Ω  |
| Operating Frequency:          | 850-2450 MHz  |
| Frequency Response:           | +/-1.5 dB (950-2150 MHz), +/-2.0 dB (850-2450 MHz)<br>+/-0.5 dB Over Any 36 MHz Channel |
| Input P1dB:                   | 0 dBm   |
| Noise Figure:                 | 14 dB @ 0 dB Gain   |
| OIP3:                         | +10 dBm   |
| Input Return Loss:            | 14 dB   |
| Output Return Loss:           | 14 dB   |
| Isolation (input-to-input):   | 60 dB   |
| Isolation (output-to-output): | 60 dB   |
| Isolation (input-to-output):  | 55 dB (950-2150 MHz), 50 dB (850-2450 MHz)  |
| Input Gain Range:             | -23.5 to +8 dB in .5 dB Steps   |
| Output Gain Range:            | -23.5 to +8 dB in .5 dB Steps   |
| Local Control:                | 8.4" Touchscreen Display  |
| Remote Control:               | SNMP, TELNET, TCP/IP, Web Browser Interface Via Ethernet                                |
| Power Requirements:           | 100-240 VAC Autoranging, 50/60 Hz   |
| Power Consumption:            | 160 W   |
| Size:                         | 4 RU: 7"H x 19"W x 23.25 D"   |

\*Specifications may vary with connector type. See individual specification sheet for specific performance data.

\*Specifications may vary with connector type and size configuration. See individual specification sheet for specific performance data.